## **Technical Data Sheet**

### Brushless motor FBM 4000 Ex























#### Advantages/characteristics:

- ▶ Brushless motor
- ▶ Increased duration possible
- ▶ Very low wear
- ▶ Maintenance-free
- ▶ Low life cycle costs
- ▶ With infinitely speed adjustment
- ▶ Very low noise level
- ▶ An extremely tough housing with double skin in aluminium
- ▶ With integrated no-volt release
- ▶ With soft-start









Technical data/type	FBM 4000 Ex			
Motor type	Single phase brushless motor			
Housing, material	Aluminium, painted			
Venting	Externally ventilated			
Motor protection	Circuit breaker			
Low-voltage protection	Yes			
Speed setting, stepless	Yes			
Power supply cable (100 - 240 V)	H 07 RN-F 3G 1,5			
Power supply cable (12 - 24 V)	_			
Power supply cable (42 V)	_			
Standard cable length (m) <sup>1)</sup>	5			
Standard plug <sup>2)</sup>	CEE 7/7 <sup>3)</sup>			
Weight (kg)	6,1			

Certificates					
Operation category as per EN 60034-1 (VDE 0530)	S1 (continuous operation)				
Protection class as per DIN EN 60 529	IP 55				
EC-type examinationcertificate number	PTB 10 ATEX 1054 X				
Operating range					
Operating temperature (°C)	-20 bis +40				

Nominal data for FBM 4000 Ex, output 600 Watt				
Nominal voltage (V)	230			
Nominal frequency (Hz)	50 - 60			
Nominal output (W)	600			
Nominal speed (R/min)	9.200			
Nominal current (A)	4,2			
Protection class	I			
Ex-marking	🐼 Ex db eb IIC T6 / T5 Gb			

<sup>1)</sup> Other cable lengths available on request


<sup>2)</sup> Other plugs available on request

<sup>3)</sup> For applications outside hazardous areas

## **Technical Data Sheet**

Brushless motor FBM 4000 Ex

#### Design:




# FBM 4000 Ex externally ventilated with double housing.

The cooling air flows through the chambers of the double housing. The interior of the motor is thereby completely protected against corrosion of electrical components, e.g. from ambient air steam, like in electroplating units.

The arrows show the direction of the cooling air through the chambers of the double housing.

#### Dimensions [mm]:



#### Motor FBM 4000 Ex with speed control and no-volt release

Voltage (Volt)	Frequency (Hz)	Output (Watt)	Cable length (m)	Plug CEE 7/7	Part no.
230 50-60	600	5	Ja	10-400 01 000	
		5	-	10-400 01 001	